



ECC99

R. F. DOUBLE TRIODE
Base: NOVAL

$U_f = 6,3$ or $12,6$ V
 $I_f = 800$ or 400 mA

Typical characteristic:

$U_a = 150$ V
 $U_g = -4$ V
 $I_a = 18$ mA
 $S = 9,5$ mA/V
 $R_i = 2,3$ K Ω
 $\mu = 22$

Limiting values:

$U_a = 400$ V
 $I_k = 60$ mA
 $U_{k/f} = 200$ V
 $W_a = 5$ W

Capacitances:

system I.	system II.
$C_g/k = 5,8$	$5,8$ pF
$C_a = 0,91$	$0,81$ pF
$C_g/a = 5,1$	$5,1$ pF

Recommended use:

Driver of power triodes such as 300 B, 2A3..., Output stage headphone amplifiers, preamplifiers, power stage little P-P triode amplifiers (10W-4XECC99) and parallel voltage power supplies. Can be used instead of 5687, E182CC, 6840, 6BL7.

Note:

Outlets on some of these types, could have different set-up.

Dimension and connections:

